



## “Safe”-style code lock

### K8082

Innovating and impressive code lock, impossible to determine the pressed keys due to the use of digital rotary encoder



### Specifications:

- User definable 4-digit code through software
- Relay output: NO/NC 3A/24VDC max.
- Power supply : 12V DC / 100mA max.
- Front panel included
- Dimensions : (front) 85x85mm ; 3,35"x3,35"  
mounting depth: 45mm ; 1,77"


### Choice of 4 operating modes:

**Mode 1:** Compose the correct code to activate relay output.

**Mode 2:** Compose the correct code to pulse relay output . (0.5 -> 9s adjustable)

**Mode 3:** Compose the correct code within 60s after power-up to keep output on. (e.g. To prevent unauthorised use of equipment)

**Mode 4:** Compose the correct code within 60s after power-up to prevent activation of output (e.g. To sound an alarm when the correct code is not entered within 60s)



### Application examples:

- Open a door, gate, fence, ...
- Arm / disarm your alarm system
- Prevent unauthorized use (mode 3) of car, entertainment systems, computers, machinery, etc...